

X16 Enhancements

Feature	System	Telephone	Description
Weekend Schedule	✓		The system can be programmed when to start and stop playing a special weekend OGM.
Holiday Schedule	✓		The system can be programmed when to start and stop playing a special holiday OGM
Recall Ringing	✓		This timer has been expanded to include a zero setting which disables CO Lines from recall ringing.
Three Ringing Scenario's	✓		<ol style="list-style-type: none"> 1) All EXT On – All extensions that are programmed to ring will ring. 2) All EXT Off – Ringing on all extensions is turned off so no extensions will ring allowing the Auto Attendant to answer all of the calls once the answer delay timer (which can be set as short as 06 seconds) has expired. 3) AA Only – Only the Attendant, as defined in the Attendant EXT#, will ring, no other extension will ring.
System OGM 60 seconds	✓		The System OGM's have now been increased to 60 seconds.
Backlit Power saver mode		✓	A parameter (LCD Backlight) has been added to the Phone Setup area of programming, which allows the user to program the LCD Backlight to power saver mode (off). In power saver mode, the LCD will automatically dim after 60 seconds.
Call Forward Timer		✓	The Call Forward timer, which is found in the Phone Setup area, has been adjusted to allow the user to select from 00 (creating an immediate forward condition) to 25 seconds before a ringing call will forward to the new destination. The function of the timer has not changed.
Caller ID enable/Disable		✓	A parameter (Caller ID) has been added to the Phone Setup area which can enable or disable caller ID from being seen on the extension; when disabled, (off) the CID is not stored, and the extension is not be allowed to enter the CID review area.
Caller ID On Call Transfer		✓	Caller ID is sent to the receiving extension when calls are transferred from the Attendant or the Auto Attendant. This means that the receiving extension will see the Caller ID prior to answering the call.
Mailbox Password		✓	A parameter (Remote Code) has been enhanced in the Voice Mail Setup area in Phone Setup, which allows the user to define the mailbox's password.
Second Call Alert		✓	A parameter (2 ND Call Beep) has been added to the Phone Setup area of programming, which allows the user to disable (off) the beep tone heard when they are on a call and a second call rings into the system.
Transfer Ringing		✓	All transferred calls an extension or auto attendant, will now ring at an extension even if the telephone is programmed not to ring when the CO line initially rings into the system.